

P2400 PowerSmart Series™ Inverter Generator Powered by Briggs & Stratton



Safe for Sensitive Electronics

The inverter technology produces smoother power. This means you can safely recharge and power your sensitive electronics such as laptops, smartphones and gaming systems.

CO Guard™ Carbon Monoxide Shutdown

Advanced Detection. Added Protection. This patent-pending technology shuts down your generator when harmful levels of carbon monoxide accumulate in the generator's operating area.

Parallel Connector Port

A dedicated parallel outlet lets you connect two units together for even more power - perfect for RVs with air conditioning units.

Parallel connector kit is sold separately.

Specifications

Starting Watts	2400
Running Watts	1800
Voltage	230
Frequency	50
Noise Level	58 DbA
Run Time	8 hours at 25% load
Outlets	2 x 230v / 1 x 12v / 2 x USB
Starter	Recoil
Engine Configuration	4 Stroke OHV
Engine Displacement	79cc
Fuel Tank Capacity	3.87Litres
Low Oil Shutdown	Yes
Weight	23 kg
Dimensions (lxwxh)	51 x 31 x 44 cms
Warranty	3 Years Consumer 1 Year Commercial

Phone: 1300 436 738 **Email:** sales@powerlite.com.au **Website:** powerlite.com.au

Address: 2 Binney Road, Kings Park NSW 2148

Powerlite Australia reserves the right to make changes in mode, technical specifications, colour configuration and accessories. Powerlite Australia Pty Limited ABN: 34 083 604 004



Powerlite Australia is an ISO9001
quality certified company

